

Frequency Converter

For high frequency internal vibrators– HJ series



type	input voltage	output voltage	power	nominal current	sockets	mass	suitable for
MUF-1	230V/50Hz	42V/200Hz	0,8 kVA	11 A	1	21kg	1x HJ50
MUF-2	230V/50Hz	42V/200Hz	1,6 kVA	21 A	2	30kg	2x HJ50 1x HJ57
MUFT-2	400V/50Hz	42V/200Hz	1,8 kVA	25 A	2	30kg	2x HJ57 1x HJ65
MUFT-3*	400V/50Hz	42V/200Hz	3,5 kVA	42 A	3	47kg	2x HJ57 HJ65+HJ57
MUFT-5*	400V/50Hz	42V/200Hz	5,0 kVA	65A	3	55kg	3x HJ65

* Ab MUFT-3 with lift truck

Above given technical performance data are non-binding average values. Subject to modifications and amendments.